



LTN3200AC/LTN3300AC 200W/300W Low Voltage AC Transformer

Job Name:

Date:

Model:

Quantity:

Features

1. Specifically designed for landscape lighting
2. Slim 304 Stainless Steel housing
3. Centered loophole and bottom support for easy installation
4. Locking hinge for cover
5. Concentric knockouts
6. LCD control panel
7. Four operational functions
 1. Photocell – “Auto” mode for dusk to dawn
 2. Timer – “Timer” mode for any time setting
 3. Astronomic Timer – “Astro” mode for timer function by geographic location
 4. ON/OFF mode
8. Daily dual timer options
9. Percent load and overload indicators
10. Overload and circuit breaker protection
11. Quick connector taps (no screwdriver needed)
12. Suitable for indoor or outdoor use



Specification

13. Input line voltage: 110-128V AC 60 Hz
14. Output Low Voltage: 12V & 15V AC
15. Output size: 25A/300VA
16. Three 12V or 15V taps
17. 5' power cord
18. ETL Listed for Landscape Lighting
19. 10 Year transformer Warranty
20. 3 Year Control Timer Warranty



Replaceable, plug-in timer



PART NUMBER	UPC	WATTS	DIMENSIONS	WEIGHT
LTN3200AC	850041316857	200	13 x 4.34 x 3.9"	14.9 lbs.
LTN3300AC	850041316864	300	13.46 x 5.12 x 4.65"	15.8 lbs.

650 Algonquin Rd, Ste 206, Schaumburg, IL 60176
PH: 847.496.5276 FAX: 846.701.8342